

				Unused_4 (U) • FeatureCfg_DPAC_LowPowerMode (FCDPACLPM) • FeatureCfg_DPAC_ParkAssistDisplay (FCDPACPAD)	
706-02-01	xx*x	xxxx	xx--	0 = U Disabled • FCDPACLPM Disabled • FCDPACPAD Disabled	8 = U Enabled • FCDPACLPM Disabled • FCDPACPAD Disabled
				2 = U Disabled • FCDPACLPM Disabled • FCDPACPAD Enabled	A = U Enabled • FCDPACLPM Disabled • FCDPACPAD Enabled
				4 = U Disabled • FCDPACLPM Enabled • FCDPACPAD Disabled	C = U Enabled • FCDPACLPM Enabled • FCDPACPAD Disabled
				6 = U Disabled • FCDPACLPM Enabled • FCDPACPAD Enabled	E = U Enabled • FCDPACLPM Enabled • FCDPACPAD Enabled
				FeatureCfg_DPAC_ParkAssistType (FCDPACPAT) • FeatureCfg_DPAC_DoorAjarInd (FCDPACDAI) • FeatureCfg_DPAC_TailgateAjarInd (FCDPACTAI)	
706-02-01	xx**	xxxx	xx--	00 = FCDPACPAT None • FCDPACDAI Disabled • FCDPACTAI Disabled	0A = FCDPACPAT Eight_CH • FCDPACDAI Enabled • FCDPACTAI Disabled
				01 = FCDPACPAT None • FCDPACDAI Disabled • FCDPACTAI Enabled	0B = FCDPACPAT Eight_CH • FCDPACDAI Enabled • FCDPACTAI Enabled
				02 = FCDPACPAT None • FCDPACDAI Enabled • FCDPACTAI Disabled	0C = FCDPACPAT Ten_CH • FCDPACDAI Disabled • FCDPACTAI Disabled
				03 = FCDPACPAT None • FCDPACDAI Enabled • FCDPACTAI Enabled	0D = FCDPACPAT Ten_CH • FCDPACDAI Disabled • FCDPACTAI Enabled
				04 = FCDPACPAT Four_CH • FCDPACDAI Disabled • FCDPACTAI Disabled	0E = FCDPACPAT Ten_CH • FCDPACDAI Enabled • FCDPACTAI Disabled
				05 = FCDPACPAT Four_CH • FCDPACDAI Disabled • FCDPACTAI Enabled	0F = FCDPACPAT Ten_CH • FCDPACDAI Enabled • FCDPACTAI Enabled
				06 = FCDPACPAT Four_CH • FCDPACDAI Enabled • FCDPACTAI Disabled	10 = FCDPACPAT Twelve_CHFLK • FCDPACDAI Disabled • FCDPACTAI Disabled
				07 = FCDPACPAT Four_CH • FCDPACDAI Enabled • FCDPACTAI Enabled	11 = FCDPACPAT Twelve_CHFLK • FCDPACDAI Disabled • FCDPACTAI Enabled
				08 = FCDPACPAT Eight_CH • FCDPACDAI Disabled • FCDPACTAI Disabled	12 = FCDPACPAT Twelve_CHFLK • FCDPACDAI Enabled • FCDPACTAI Disabled
				09 = FCDPACPAT Eight_CH • FCDPACDAI Disabled • FCDPACTAI Enabled	13 = FCDPACPAT Twelve_CHFLK • FCDPACDAI Enabled • FCDPACTAI Enabled

Change From: 7327 FFC4 01

27 = 2 + 07 = (U Disabled • FCDPACLPM Disabled • FCDPACPAD Enabled)

AND

(FCDPACPAT Four_CH • FCDPACDAI Enabled • FCDPACTAI Enabled)

Change To: 736B FFCC 41

6B = 6 + 0B = U Disabled • FCDPACLPM Enabled • FCDPACPAD Enabled

AND

FCDPACPAT Eight_CH • FCDPACDAI Enabled • FCDPACTAI Enabled

RESULT: Enabled FCDPACDAI and went from 4 channel to 8 channel